

# AP-EIP60

## Emergency Call IP Phone

High Performance Emergency Call IP Phone Solution



Smart Web Manager

**AddPac**

**AddPac Technology**

Sales and Marketing

# Contents

- Main Screen
- System
  - Language
  - LAN Setup
  - DACS
  - Display
  - File Browser
- SIP Call & Media
  - SIP (Session Initiation Protocol)
  - Speed Dial
  - Media
- Miscellaneous
  - Door Control and Test
  - Network Test



# Main Screen

Initialization

Rebooting

Save

Smart Web Manager  
www.addpac.com

**System**

- Language
- WAN Setup
- NTP
- System Time
- File Browser
- Auto Upgrade

**Basic**

- Protocol
- Server SIP**
- SIP Registration
- SPEECH Extension
- DTMF/CODEC
- VoIP Dial Plan
- Static Route
- Hot Line

**Advanced**

- Port Control
- Service
- Filtering
- Security
- DSCP
- EMS

**Miscellaneous**

- Port & Call Status
- System Status
- Call Log
- System Log
- Ping

### SIP (Session Initiation Protocol)

Use SIP Server  Yes  No

Primary SIP Server   Server address and Port (default 5060)

Secondary SIP Server   Server address and Port (default 5060)

Local Domain Name  (SIP userpart of authentication)

SIP Signaling Port  (default 5060, between 1 to 65535)

Register Expiration  (in seconds, default 60, between 10 to 86400)

Session Re-Fresh  INVITE  UPDATE

Session Expire Time  (in seconds, default 1800, between 30 to 86400, 0 = disable)

Min SE  (in seconds, default 1800, between 30 to 86400)

Apply

**Information**

AddPac Technology  
Model : EIP60\_G2  
H/W Version : 2.0  
S/W Version : 8.50.001  
Smart Web Version : 0.4  
Smart Web Build : Dec 23 2016  
Voice Interface  
SPE(1)O(1)  
Protocol : SIP  
Status : Unregistered  
Current Calls: 0  
CallNetwork : Static  
172.17.208.21  
Mac Address: 0002.a4fc.00ff

**Description**

Configure the settings for SIP.  
Contact your service provider for the settings

Menu Tree

Output Screen after  
Menu Select

System Information  
and Help Message

# System Information

**Smart Web Manager**  
www.addpac.com

**System Information**

H/W Version	2.0
S/W Version	8.50.001
MAC Address	0002.a4fc.00ff
VoIP Protocol	SIP
Voice Interface Module	SPE(1)O(1)
Registration Status	<b>Unregistered</b>
Supported Codec List	
Network Information	Static 172.17.208.21
WAN LINK Status	100Mbps FULL Duplex Link UP
Current Time	Fri Dec 23 11:01:01 2016
System Startup Time	Fri Dec 23 10:41:28 2016
System Running Time	0 days 00:19:33
Total Calls	0

**Information**

AddPac Technology  
Model : EIP60\_G2  
H/W Version : 2.0  
S/W Version : 8.50.001  
Smart Web Version : 0.4  
Smart Web Build : Dec 23 2016  
Voice Interface  
SPE(1)O(1)  
Protocol : SIP  
Status : Unregistered  
Current Calls : 0  
CallNetwork : Static  
172.17.208.21  
Mac Address: 0002.a4fc.00ff

**Description**


Software Version Information and SIP Server Connection Info. Display, etc

# Language

**Configure Language**

한국어

English

 Apply

Language Configuration for Smart Web Manager, English is default Language.  
Other Language such as Russia will be add.

# LAN Setup

**LAN Setup**

System Name Configuration

LAN Setup

Hostname

Static IP  DHCP

IP Address  A.B.C.D

Network Mask  A.B.C.D

Default Router  A.B.C.D

DNS Server  Primary DNS Server

Secondary DNS Server

VLAN

AP-VAC50  
Static IP Configuration.  
Input following  
Information (IP Address,  
Network Mask  
Default Router  
DNS Server )

Dynamic IP address  
Configuration using  
DHCP Protocol

VLAN Configuration  
(ID : 2~4096)

# SIP(Session Initiation Protocol)

## SIP (Session Initiation Protocol)

SIP server check if exist.

SIP Basic Information Display

Telephone Line Number and Password Configuration Same Information is used when DACS is connected

Use SIP Server

Yes  No

Primary SIP Server

172.17.250.250 5060 Server address and Port (default 5060)

Secondary SIP Server

5060 Server address and Port (default 5060)

Local Domain Name

(SIP userpart of authentication)

SIP Signaling Port

5060 (default 5060, between 1 to 65535)

Register Expiration

60 (in seconds, default 60, between 10 to 86400)

Session Re-Fresh

INVITE  UPDATE

Session Expire Time

1800 (in seconds, default 1800, between 30 to 86400, 0 = disable)

Min-SE

1800 (in seconds, default 1800, between 30 to 86400)

Extension

1020 Extension Number, Password

# SIP Registration

The screenshot shows the 'SIP Registration' configuration page in the Smart Web Manager. The page is divided into several sections:

- System:** Language, WAN Setup, NTP, System Time, File Browser, Auto Upgrade.
- Basic:** Protocol, Server SIP, **SIP Registration**, SPEECH Extension, DTMF/CODEC, VoIP Dial Plan, Static Route, Hot Line.
- Advanced:** Port Control, Service, Filtering, Security, DSCP, EMO.
- Miscellaneous:** Port & Call Status, System Status, Call Log, System Log, Ping.

The main configuration area is titled 'SIP Registration Configuration' and contains a table with the following data:

Pots Num	Port	E.164 Number	User Name	Password	DisplayName	HuntStop	Reg
0	S0P0	2121				<input type="checkbox"/>	<input checked="" type="checkbox"/>

Below the table, there is a red warning message: '\* SIP Registration - Assigned Pots Tag Number : 0 - 4'. An 'Apply' button with a green checkmark is visible.

The right sidebar contains two sections:

- Information:** AddPac Technology, Model : EIP60\_G2, H/W Version : 2.0, S/W Version : 8.50.001, Smart Web Version : 0.4, Smart Web Build : Dec 23 2016, Voice Interface SPE(1)O(1), Protocol : SIP, Status : Unregistered, Current Calls : 0, CallNetwork : Static 172.17.208.21, Mac Address : 0002.a4fc.00ff.
- Description:** Set up for using FXS port to registration SIP Server.



# VoIP Dial Plan

Smart Web Manager  
www.addpac.com

**System**

- Language
- WAN Setup
- NTP
- System Time
- File Browser
- Auto Upgrade

**Basic**

- Protocol
- Server SIP
- SIP Registration
- SPEECH Extension
- DTMF/CODEC
- VoIP Dial Plan**
- Static Route
- Hot Line

**Advanced**

- Port Control
- Service
- Filtering
- Security
- DSCP
- EMS

**Miscellaneous**

- Port & Call Status
- System Status
- Call Log
- System Log
- Ping

## VoIP Dial Plan / Prefix

**Plan Table**

Rule Num	Digits to Insert	Digits to delete	Digit Pattern	Control
				Delete
	<input type="text"/>	<input type="text"/>	<input type="text"/>	Add

**Prefix Table**

Voip Num	Prefix	Called Num Plan	Calling Num Plan	Hunt Stop	Control
	<input type="text"/>	N.A.	N.A.	<input type="checkbox"/>	Delete
	<input type="text"/>	N.A.	N.A.	<input type="checkbox"/>	Apply

\* VoIP Dial Plan - Assigned Translation-Rule Tag Number : 0 - 99  
\* VoIP Dial Plan - Assigned VoIP Tag Number : 10000 - 10099

**Information**

AddPac Technology  
Model : EIP60\_G2  
H/W Version : 2.0  
S/W Version : 8.50.001  
Smart Web Version : 0.4  
Smart Web Build : Dec 23 2016  
Voice Interface  
SPE(1)O(1)  
Protocol : SIP  
Status : Unregistered  
Current Calls : 0  
CallNetwork : Static  
172.17.208.21  
Mac Address : 0002.a4fc.00ff

**Description**

Configure the settings for VoIP Dial Plan and Prefix table

# Service

The screenshot shows the 'Service' configuration page in the Smart Web Manager. The page is divided into several sections: System, Basic, Advanced, and Miscellaneous on the left sidebar. The main content area is titled 'Service' and contains the following configuration options:

- Application Services:**
  - Enable Telnet: Server Port  (default 23, 1-65535)
  - Enable HTTP: Server Port  (default 80, 1-65535)
  - Enable FTP: Control Port  (default 21, 1-65535), Data Port  (default 20, 1-65535)
  - Enable Syslog: Primary Server , Secondary Server , Port  (default 514), Log Level , Log Command
- Timer:**
  - Inter Digit Time:  sec (default 3, 1-600)
  - Hook-Flash-Detect:  ms (default 700, 200-1100)
- Call Service:**
  - Transfer:  Hook-Flash  Not-assigned
  - Hold:  Hook-Flash  Not-assigned
- SIP Transfer:**
  - Mode:  blind  Attended
- Hunt:**
  - Algorism:
- Change Password:**
  - ID: root, New Password , Confirm Password

An 'Apply' button is located at the bottom left of the configuration area.

**Information:**  
AddPac Technology  
Model : EIP60\_G2  
H/W Version : 2.0  
S/W Version : 8.50.001  
Smart Web Version : 0.4  
Smart Web Build : Dec 23 2016  
Voice Interface  
SPE(1)O(1)  
Protocol : SIP  
Status : Unregistered  
Current Calls : 0  
CallNetwork : Static  
172.17.208.21  
Mac Address: 0002.a4fc.00ff

**Description:**  
Enable or disable Telnet, HTTP, FTP and specify the access port and Call Hold/ Transfer and Timer .



# Thank you!

**AddPac Technology Co., Ltd.**  
Sales and Marketing

Phone +82.2.568.3848 (KOREA)

FAX +82.2.568.3847 (KOREA)

E-mail [sales@addpac.com](mailto:sales@addpac.com)