
Category	S/W Release Version	Date
H.323	v6.06	14.Feb. 2003

Resources Available Indication is supported

When any monitored H.323 resources exceed the threshold level defined by the high parameter, the gateway sends an RAI message to the gatekeeper with the AlmostOutOfResources field flagged. This message reports high-resource usage.

When all gateway H.323 resources drop below the level defined by the low parameter, the gateway sends the RAI message to the gatekeeper with the AlmostOutOfResources field cleared. Using this report, the gatekeeper choose proper gateway among gateways that have same destination.

This feature is applied to all Voicefinder VoIP gateway models.

- Related Commands

Below commands are configuration commands for RAI

```
ap2520-A(config)# gateway
ap2520-A(config-gateway)# resource ?
threshold      set sending RAI and threshold

ap2520-A(config-gateway)# resource threshold ?
<1-100>        high threshold value (default 90)

<cr>
ap2520-A(config-gateway)# resource threshold 90 ?
<1-100>        low threshold value (default 70)

<cr>
ap2520-A(config-gateway)# resource threshold 90 70
ap2520-A(config-gateway)# no resource threshold
```

- Default value

RAI sending is disabled.